DIGITUS®

BEZDRÁTOVÝ 300N USB 2.0 INTERNETOVÝ ADAPTÉR



Průvodce rychlou instalací DN-70542 Rev.2 • DN-70543 Rev.2

Instalace ovladače

K instalaci bezdrátového USB adaptéru proveďte níže uvedené pokyny:

- Vložte bezdrátový USB síťový adaptér do dostupného USB 2.0 portu vašeho počítače. Uvědomte si prosím, že USB konektor je směrový proto prosím obraťte USB adaptér, jestliže ho nelze vložit do USB portu.
- 2. Na vašem počítači se objeví následující zpráva, klikněte na '<u>Cancel /</u> <u>Close (storno/uzavřít)</u>'.

Instalace u Windows XP

Hardware Update Wizard	
	Welcome to the Hardware Update Wizard Windows will search for current and updated software by looking on your computer, on the hardware installation CD, or on the Windows Update Web site (with your permission). Read our privacy policy
	Can Windows connect to Windows Update to search for software? Yes, this time only Yes, now and every time I connect a device No, not this time
	Click Next to continue.
	< Back Next > Cancel

Instalace u Windows Vista a Windows 7/8/10

Driver Software Installation		×
Installing device driver so	ftware	
802.11 n WLAN	Waiting for user input	
		Close

 Vložte CD s ovladačem do vaší jednotky CD-ROM. Objeví se níže uvedená obrazovka automatického spuštění. Jestliže se neobjeví, klikněte dvakrát na '<u>autorun.exe</u>' na CD.



Klikněte na 'Install Driver (instalace ovladače)' k spuštění instalačního programu.

4. Objeví se průvodce instalací. K pokračování klikněte na "Next" (pokračovat).



 Vložte bezdrátový USB síťový adaptér (DN-70542/DN-70543) do USB 2.0 portu vašeho počítače, systém si vyhledá nový hardware a automaticky provede instalaci ovladačů.



 Po ukončení instalace se objeví zpráva vyžadující restart počítače. Můžete kliknout na '<u>Finish (ukončení instalace)</u>' a restartovat počítač k ukončení instalace ovladače.



7. Po ukončení instalace ovladače klikněte na utilitu adaptéru z vašeho hlavního panelu nebo ze složky programů. Klikněte na "available networks" (dostupné sítě), vyberte bezdrátový přístupový bod, ke kterému se připojíte a stiskněte tlačítko "Add to Profile" (přidat k profilu).

REALTEK 11n USB Wireless LAN Utility				
Refresh(R) Mode(M) Abou	t(A)			
🖃 🦞 MyComputer	General Profile Available Network Status Statistics Wi-Fi Protect Setup			
Realtek RTL818	Available Network(s)			
	SSID Channel Encryption Network Authentication	Signal 1		
	PHLY96C 1 AES WPA Pre-Shared Key	88% Ir		
	1 ⁰ NETCORE 1 None Unknown	42% Ir		
	1 ⁹⁹ HLY3F 6 TKIP WPA Pre-Shared Key	26% Ir		
	1 ²⁹ QA300M 6 None Unknown	58% Ir		
	11 Marza Unknown	8% Ir		
		02% Ir		
		92.70 1		
		>		
	Refresh Add to Profile	ן ו		
		,		
	Note			
	Double click on item to join/create profile.			
🔽 Show Tray Icon	🔲 Disable Adapter	Close		
🗌 Radio Off	Windows Zero Config			

8. V případě potřeby vyplňte bezpečnostní informace a poté klikněte na "OK" pro připojení k bezdrátové síti.

Vireless Network Properties:			
Profile Name: HLY96C	802.1x configure		
Network Name(SSID): HLY96C	EAP TYPE :		
	GTC		×
	Tunnel :	Privision Mode	э:
This is a computer-to-computer(ad hoc) network access points are not used.	;; wireless	×	~
Channel: 1 (2412MHz) V	Username :		
Wireless network security			
This network requires a key for the following:	Identity :		
Network Authentication: WPA-PS	ж 💌		
Data encryption: AES	Domain :		
	Password :		
Key index (advanced): 1 🗸	Certificate :		
Network key:			~
*******	PAC : .	Auto Select PAC	
Confirm network key:			~

OK Cance			

9. Po úspěšném navázání připojení se objeví stavová obrazovka.

🌲 REALTEK 11n USB W	ireless LAN Utility	
Refresh(R) Mode(M) Abou	Jt(A)	
🖃 🦞 MyComputer	General Profile Available Network Status Statistics Wi-Fi Protect Setup	
Realtek RTL818t		
	Status: Associated	
	Speed: Tx:150 Mbps Rx:150 Mbps	
	Type: Infrastructure	
	Encryption: AES	
	SSID: HLY96C	
	Signal Strength:	
	Link Quality:	
	gg%	
	Network Address:	_
	MAC Address: 00:E0:4C:71:00:01	
	IP Address: 192.168.1.139	
	Subnet Mask: 255.255.255.0	
	Gateway:	
	DeMour ID	
	Keivew IP	
<		
Show Tray Icon	, Disable Adapter	Close
Radio Off	🗌 Windows Zero Config	